


10 GA WIRE
SEW

#6073 FUSE BLOCK (2 EA)
600V 30A 3P
USES (6) 30A
CLASS CC FUSES #6076-1



CONTROL WIRING NOTE

ALL CONTROL WIRES
#20 AWG #4609
UNLESS OTHERWISE NOTED

POWER REQ'TS

208 VOLTS
1 PHASE
60 HERTZ
79 AMPS
16432 WATTS




CAUTION

TO PROVIDE CONTINUED
PROTECTION AGAINST THE
RISK OF ELECTRIC SHOCK,
CUSTOMER'S POWER
SUPPLY MUST BE
PROPERLY GROUNDED.

WIRE SIZES

NOTE: ALL WIRES TO BE
TYPE SEW/SF2, #10 AWG
MINIMUM UNLESS NOTED

#6311
30A RELAY
208-240V
COIL
DPST-NO



#20 GA
#4609

#6344-1
CONTROL
POWER
ON/OFF
SWITCH
10AMP 240V

#6355
30A RELAY
W/12V
DC COIL

TYPE K T/C
6750-2

#6060-1
#22GA WIRE
MULTI-COND

#6778-CONTROL
TRANSFORMER
OUTPUT-24VAC

FUSE
#6726
1/2 AMP

SENTRY 2.0
CONE FIRE

TO RE-ORDER ELEMENTS, SPECIFY		
DESCRIPTION	QTY	LDC
EL 704111BASTB	4	SIDE-TOP/BOT
EL 704111BASM	2	SIDE-MID

UL/CUL LISTED

2350°F

REV	DATE	BY	DESCRIPTION
-	02-14-01	RLG	
A	12/02/02	ITB	MOVED FUSE TO TRANS LEAD
B	6/2/03	ITB	MOVED SW TO CENTER RELAY

SWITCH BOX ASSY-40986-2
PARAGON INDUSTRIES
2011 SOUTH TOWN EAST BLVD
MESQUITE, TEXAS 75149

WIRING DIAGRAM
208V, 1 PHASE, 60HZ, 16432W

PART NO.	REV
704111BA00	B
DRAGON 242724	