




TO RE-ORDER ELEMENTS, SPECIFY		
DESCRIPTION	QTY	LOC
EL306111ETB	4	TOP/BOT
EL306111EM	2	MID

WIRE SIZES

NOTE: ALL WIRES TO BE TYPE SEW/SF2, #10 AVG MINIMUM UNLESS NOTED

#6311
30A RELAY
208-240V
COIL
DPST-NO



10 GA WIRE
SEW

#6073 FUSE BLOCK (2 EA)
600V 30A 3P
USES (6) 30A
CLASS CC FUSES #6076-1

PWR CONN BLOCK

POWER REQ'TS
240 VOLTS
1 PHASE
60 HERTZ
60 AMPS
14400 WATTS

#6311-1
CONTROL
POWER
BUCKET
RATED
11AMP 240V

CONTROL WIRING NOTE

ALL CONTROL WIRES
#20 AVG #4609
UNLESS OTHERWISE NOTED

#20 GA
#4609

CAUTION

TO PROVIDE CONTINUED PROTECTION AGAINST THE RISK OF ELECTRIC SHOCK, CUSTOMER'S POWER SUPPLY MUST BE PROPERLY GROUNDED.

#6355
30A RELAY
V/12V
DC COIL

FUSE #6726
1/2 AMP

#6770-CONTROL
TRANSFORMER
OUTPUT-24V AC

TYPE K T/C
6750-1

CONE FIRE
SENTRY 2.0

UL/CUL LISTED

2350°F

REV	DATE	BY	DESCRIPTION
-	2/3/02	DTB	

SWITCH BOX ASSY- 42017-4

PARAGON INDUSTRIES
2011 SOUTH TOWN EAST BLVD
MESQUITE, TEXAS 75149

WIRING DIAGRAM

240V, 1 PHASE, 60HZ, 14400WATTS

PART NO. 306111EA00

VIK283-SEN-C

REV -